

2 in 1



USER MANUAL

RW 100

Wireless Mini Router/Repeater

INDEX

| | |
|--|----|
| General Information | 3 |
| Introduction | 4 |
| Getting Started | 6 |
| How Connect to Wlan Mini Router/Repeater RW100. | 8 |
| Configuring via Web Browser | 12 |
| Firmware Upgrade. | 24 |
| Factory Default and Settings Backup, Restore. | 26 |
| How to connect your computer/laptop with the Wireless Mini Router/Repeater RW 100 | 28 |
| How to configure your computer/laptop with the Network IP Address . . . | 32 |

GENERAL INFORMATION

This product includes software codes developed by third parties. These software codes are subject to either the GNU General Public License (GPL), Version 2, June 1991 or the GNU Lesser General Public License (LGPL), Version 2.1, February 1999. You can copy, distribute, and/or modify in accordance with the terms and conditions of GPL or LGPL.

The source code should be complete, if you think our need to provide any additional source code files under GNU General Public License (GPL), please contact us. We are committed to meeting the requirements of the GNU General Public License (GPL) . You are welcome to contact us local office to get the corresponding software and licenses. Please inform us your contact details and the product code. We will send you a CD with the software and license for free.

Please refer to the GNU GPL Web site for further information.

<http://www.gnu.org/licenses/licenses.en.html>.

INTRODUCTION

The Wireless Router/ Repeater RW 100 from Schwaiger is a combined wired/ wireless network connection device designed specifically for small business, office, and home office networking requirements. It complies with the IEEE 802.11n standard. It adopts MIMO as well as SST technologies. It also works well with other 11b/g and 11n protocol wireless products. Create instant WiFi hotspots at any location where you have Internet connection.

Main Features

- ✓ Complies with IEEE 802.11b/g/n standards (up to 300 Mbps)
- ✓ Supports Router, Client, Bridge, Repeater, AP mode
- ✓ QoS function assures the quality of VoIP and multimedia streaming
- ✓ Compact and portable, powerful wireless signal as well
- ✓ Travel size design, ideal for home or travel use
- ✓ Supports WEP, WPA/WPA2, WPA-PSK/WPA2-PSK encryptions
- ✓ Power: 100 - 240 V, 50/60 Hz, 50 mA

Package Contents

Before you starting to use this router, please check if there's anything missing in the package, and contact your dealer of purchase to claim for missing items:

- » 1 x Wireless Router/ Repeater RW 100
- » 1 x Quick Installation Guide
- » 1 x RJ-45 Networking Cable

GETTING STARTED

Setting up a Wireless Infrastructure Network



For a typical wireless setup at home (as shown above), please do the following:

1. You will need broadband Internet access (a ADSL, Cable Modem line into your home or office).
2. Consult with your ADSL or Cable Modem provider for proper installation of the modem.
3. Connect the ADSL or Cable modem to the Wireless N Mini Router. Plug the power plug of the Router in electrical wall socket.
4. Adding computers to the Wireless N Mini Router.

IMPORTANT NOTE

*You can reset your WiFi Router to default setting by press and hold the 'RESET' button inside the tiny hole for 8 ~10 seconds.
You can use this solution if you forget your password.*

HOW CONNECT TO WLAN MINI ROUTER/REPEATER RW100

You can configure the Wireless-N Mini Router by connecting it with your computer/laptop with enclosed RJ45 cable or wirelessly.

- A1. Plug the Wlan Router/ Repeater RW100 to a wall socket and switch it on. (switch on the right side of the device)
- A2. Click on the network icon  (for wireless) or  (for wired connection) on the right bottom of your desktop. You will find the signal from the WLAN Mini Router/Repeater RW 100. Click on '**Connect**' then wait for a few seconds.



A3. Open web browser and type **http://192.168.10.1** in the browser's address box. This number is the default IP address for this device.



NOTE

*Please check whether the Wireless-N Mini Router accord with factory default settings once you can't download **http://192.168.10.1**. If you are still not sure what reasons, you can reset the Wireless-N Mini Router, just need to press the **,Reset'** button for **10 seconds**,*

then try again.

- A4. The login screen below will appear. Enter the "User Name" and "Password" then click "OK" to login. The default User name is "admin" and Password is "admin".

Language:

Quick Setup

Router: **AP**

Repeater: **WDS**



Wireless Basic Settings



LAN setting

Management

Administration Time Zone

Backup/Reset Upgrade

Current Mode → Router

| Wireless Network | |
|--------------------|-------------------|
| Mode | AP |
| Band | 2.4 GHz (B-G-N) |
| SSID | Schwaiger RW100 |
| Channel Number | 5 |
| Encryption | WPA2 |
| Mac | 8C:2F:54:9E:2F:88 |
| Associated Clients | 1 |

CONFIGURING VIA WEB BROWSER

After you successfully login, you can click the Wizard's menu to quickly configure your Router.



Choose the Operation Mode you need, and then click **it**.

| Mode | Description |
|----------|---|
| Router | Standard Wireless Router Mode: This router connect to Internet by WAN port, and then other terminal devices can connect to this router by wireless connection or connect to this router's LAN port by wired |
| AP | Traditional wired router realize wireless function: This router can connect to uplink router's LAN port by wired connection, user terminal can connect to this router by wireless connection |
| Repeater | Extend wireless signal comprehensively: This router can connect to uplink wireless router by wireless connection, user terminal can connect to this router by wired or wireless connection |
| WISP | Wireless used as WAN port: This router can connect to uplink wireless router by wireless connection, at the same time, it can extend wireless signal for other devices' connection |

Router Mode

Quick Setup--help you setup the router quickly

Automatically obtain an IP Address (dynamic IP)
 ADSL Dial-up (PPPoE)

SSID
Security Mode

Choose your WAN Connection Type.

If **Dynamic IP** is selected, the Router gets the IP address automatically from the DHCP server or the ISP. No configuration should be set and you can go on with the wireless configuration.

If **ADSL Dial-up (PPPoE)** is selected, please enter the **User Name** and **Password** from your ISP, These fields are case-sensitive.

Set the wireless parameter. It's recommended that you rename an **SSID**, choose a **Security Mode** and enter a **Key**.

| | |
|---------------|--|
| SSID | the "SSID" of your wireless network |
| Channel | Auto (recommend) |
| Security type | Setup the wireless security and encryption to prevent from unauthorized access and monitoring. Supports 64/128-bit WEP, WPA, WPA2, WPA/WPA2 encryption methods. |
| Security key | the "Password" of your wireless network. |

Click '**Save&Reboot**' button, It will restart.

Wait for a few seconds your Wi-Fi Router is ready for use.

AP Mode

Quick Setup -- Access Point mode

SSID

Channel

Security Mode

Set the wireless parameter. It's recommended that you rename an **SSID**, choose a **Security Mode** and enter a **Key**.

| | |
|---------------|--|
| SSID | the "SSID" of your wireless network |
| Channel | Auto (recommend) |
| Security type | Setup the wireless security and encryption to prevent from unauthorized access and monitoring. Supports 64/128-bit WEP, WPA, WPA2, WPA/WPA2 encryption methods. |
| Security key | the "Password" of your wireless network. |

Click '**Save&Reboot**' button, It will restart.

Wait for a few seconds your Wi-Fi Router is ready for use.

Repeater Mode

Quick Setup -- Repeater mode

Refresh

| SSID | Mac | Channel | Encrypt | Signal | Select |
|------------|-------------------|------------|------------------|--------|--------|
| PM7390 | 08:9E:d7:b1:22:4e | 8 B+G+N | WPA2-PSK | 100% | Select |
| dlink-4731 | cc:b2:55:a3:47:31 | 5 B+G+N | WPA-PSK/WPA2-PSK | 95% | Select |

Save&Reboot

Select the **SSID** of the target network and click **Select**.

Quick Setup -- Repeater mode

Refresh

Connect to

FM7290

SSID

Schwaiger RW100

Key

Unmask

Save&Reboot

The target network's SSID will be automatically filled into the wireless setting figure. Then enter the Password. Make sure that you use the same password for the network's SSID as the original Network you want to expand your WLAN signal performance.

Click '**Save&Reboot**' button, It will restart.

Wait for a few seconds your Wi-Fi Router is ready for use.

WISP Mode

In this mode, all Ethernet ports are bridged together and the wireless client will connect to ISP access point.

Quick Setup -- WISP

Expand Wireless Network

Wireless Expansion Enable

Refresh

| SSID | Mac | Channel | Encrypt | Signal | Select |
|------------|-------------------|------------|------------------|--------|--------|
| PM7390 | 08:96:d7:b1:22:4e | 8 8+G+N | WPA2-PSK | 100% | Select |
| dlink-4731 | cc:b2:55:d3:47:31 | 5 8+G+N | WPA-PSK/WPA2-PSK | 95% | Select |

Save&Reboot

Select the **SSID** of the target network and click **Select**.

Quick Setup -- WISP

Expand Wireless Network

Wireless Expansion Enable

Refresh

SSID PM7390

Key Unmask

Save&Reboot

The target network's SSID will be automatically filled into the wireless setting figure. Then enter the Password.

Click '**Save&Reboot**' button, It will restart.

Wait for a few seconds your Wi-Fi Router is ready for use.

CHANGE MANAGEMENT PASSWORD

Default password of Wireless-N Mini Router is “**admin**”, and it’s displayed on the login prompt when accessed from web browser. There’s a security risk if you don’t change the default password, since everyone can see it. This is very important when you have wireless function enabled.

To change password, please follow the following instructions: Please click ‘**Administrator**’ menu on the web management interface, the following message will be displayed on your web browser:

Router Management

Router Username :

New Password :

Re-enter to confirm :

Apply

Reset

If you want to change password, fill in the **Username** and **Password**.

Click '**Apply**' button, The WiFi Repeater will log off.

FIRMWARE UPGRADE

The system software used by this router is called as 'firmware', just like any applications on your computer, when you replace the old application with a new one, your computer will be equipped with new function. You can also use this firmware upgrade function to add new functions to your router, even fix the bugs of this router.

The upper right corners please click '**Firmware**', and then the following message will be displayed on your web browser:



The screenshot shows a web browser window with a title bar that reads "Firmware Upgrade". The main content area has a light gray background and contains the following elements:

- A label "Firmware Version :" followed by the text "MRE2-B1.344.0.20140217".
- A label "Select File:" followed by a text input field and a "Browse" button.
- A large "Upgrade" button centered at the bottom of the form area.

Click '**Browse**' button first; you'll be prompted to provide the filename of firmware upgrade file. Please download the latest firmware file from our website, and use it to upgrade your router.

After a firmware upgrade file is selected, click '**Upgrade**' button, and the router will start firmware upgrade procedure automatically. The procedure may take several minutes, please be patient.

NOTE

Never interrupt the upgrade procedure by closing the web browser or physically disconnect your computer from router. If the firmware you uploaded is corrupt, the firmware upgrade will fail, and you may have to return this router to the dealer of purchase to ask for help. (Warranty voids if you interrupted the upgrade procedure).

FACTORY DEFAULT AND SETTINGS BACKUP, RESTORE

You can backup all Setting of this router to a file, so you can make several copied of router configuration for security reason.

To backup or restore router setting, please follow the following instructions: Please click '**Save/Reload setting**' located at the web management interface, then the following message will be displayed on your web browser:







The screenshot shows a web interface titled "Configuration". It contains three main sections:

- Save Settings to File :** A button labeled "Save..."
- Load Settings from File :** A text input field, a "Browse" button, and an "Upload" button.
- Reset to Default Settings** (button)


| | |
|-----------------------|--|
| Save Settings to File | Press ' Save... ' button, you can please save it as another filename for different versions, and keep it in a safe place. |
| Load Settings | Press ' Browse... ' to pick a previously-saved configuration file from your computer, and then click 'Upload...'. After the configuration is uploaded, the router's configuration will be replaced by the file you just uploaded. |
| Reset Settings | Click this ' Reset to Default Settings ' button to remove all settings |

HOW TO CONNECT YOUR COMPUTER/LAPTOP WITH THE WIRELESS MINI ROUTER/REPEATER RW 100


Adding a Wireless computers to the RW 100

1. Turn on the computer.
2. Open Connect to a Network by right-clicking the network icon  (for wireless connection) or  (for wired connection) in the notification area.
3. Choose the wireless network from the list that appears, and then click **Connect**.
4. Type the network security key or passphrase if you are asked to do so, and then click **OK**. You'll see a confirmation message when you are connected to the network.
5. To confirm that you added the computer, do the following:
Open Network by clicking the **Start** button , and then clicking **Control Panel**. In the search box, type **network**, and then, under Network and Sharing Center, click **View network computers and devices**. You should see icons  (wireless connection) for the computer you added and for the other computers and devices that are part of the network.

**NOTE**



If you don't see icons  (wireless connection) in the Network folder, then network discovery and file sharing might be turned off.

Adding a Wireless computers to the Wireless Mini Router/ Repeater RW 100 with WPS Button

1. Turn on the computer.
2. Press the **WPS** button of the Wireless Mini Router/Repeater RW 100 directly for **2 – 3 seconds**.
3. Press the **WPS** button of the Wireless Adapter directly for **2 - 3 seconds**. Click **Finish** to complete the WPS configuration. (Please check your Wireless adapter Manual with WPS configuration.)
4. You should see icons  (wireless connection) for the computer you added and for the other computers and devices that are part of the network.

Adding a wired (Ethernet) computer to the Wireless-N Mini Router

1. Plug the Wireless Mini Router/Repeater RW 100 to a wall socket. Connect your computer /laptop with the Wireless Mini Router/Repeater RW 100 with enclosed RJ45 Cable.

2. To confirm that you added the computer, do the following: Open Network by clicking the **Start** button , and then clicking **Control Panel**. In the search box, type **network**, and then, under Network and Sharing Center, click **View network computers and devices**. You should see icons  for the computer you added and for the other computers and devices that are part of the network.

For more information:

<http://windows.microsoft.com/en-US/windows7/Add-a-device-or-computer-to-a-network>

<http://windows.microsoft.com/en-US/windows7/Setting-up-a-wireless-network>

<http://windows.microsoft.com/en-US/windows-vista/Setting-up-a-wireless-network>

HOW TO CONFIGURE YOUR COMPUTER/LAPTOP WITH THE NETWORK IP ADDRESS

1. Turn on the computer.
2. Click the **"Start"** button (it should be located at the lower-left corner of your screen), then click **"Control Panel"**. Click **"View Network Status and Tasks"**, and then click **"Manage Network Connections"**. Right-click **"Local Area Network"**, then select **"Properties"**. When the **"Local Area Connection Properties"** window appears, select **"Internet Protocol Version 4 (TCP/IPv4)"** and then click **"Properties"**.



3. Setting IP address manually:
Type IP address is **192.168.10.x** (x is from 2 to 252), and Subnet mask is **255.255.255.0**. Type the Router's LAN IP address (the default IP is **192.168.10.253**) into the Default gateway field.



NOTES

NOTES
