



★ ★ ★  
PROFESSIONAL



## SAT Multi Switch 9 → 8

This SCHWAIGER® multi switch is used to distribute digital signals of 2 satellite positions to up to 8 subscribers. You can feed 2 Quattro LNBs as well as terrestrial signals. All subscribers can make use of the entire range of programmes independently from one

another. A special feature of this multi switch are the differently coloured connections to avoid mix-ups upon installation.



### ARTICLE INFORMATION

Article Nr SEW4098 531  
EAN 4004005409802



Last updated: 24.07.2019



## FEATURES (SEW4098 531)

- multi switch distributes 2 satellite positions to 8 outputs
- can be fed with terrestrial signals (passive)
- independent reception of all available programmes for every subscriber
- content: 1x SAT multiswitch

## TECHNICAL DATA

|                      |   |                       |                            |
|----------------------|---|-----------------------|----------------------------|
| Quality              | PROFESSIONAL  | Power consumption     | through LNB (max.) 1000 mA |
| Colour               | black/silver  | Power supply          | 230 V AC                   |
| Point of use         | indoor use  | Power consumption     | max. 60 W                  |
| Connections (input)  | 8x F jack (75 ohms) (SAT)<br>1x F jack (75 ohms) (TV / radio) | Operating temperature | -10 bis +50 °C             |
| Connections (output) | 8x F jack (75 ohms)   | Power supply unit     | integrated                 |
| Output level (max.)  | (typ.) 100/85 dB $\mu$ V (SAT/terrestrial)                    | Dimensions (width)    | 345 mm                     |
| Frequency range      | 47 - 862 MHz<br>950 - 2150 MHz                                | Dimensions (height)   | 120 mm                     |
| Transmission loss    | (typ.) 0 dB (SAT)<br>(typ.) 23 dB (TV/FM)                     | Dimensions (depth)    | 68 mm                      |
|                      |   | Packaging             | clamshell SF               |