



☆☆☆
PROFESSIONAL



SAT Multi Switch 5 → 6

This SCHWAIGER® multi switch is used to distribute digital signals of 1 satellite position to up to 6 subscribers. You can feed signals from a Quattro LNB as well as terrestrial signals. All subscribers can make use of the

entire range of programmes independently from one another.



ARTICLE INFORMATION

Article Nr SEW4056 531
EAN 4004005405620



Last updated: 24.07.2019



FEATURES (SEW4056 531)

- multi switch distributes 1 satellite position to 6 outputs
- can be fed with terrestrial signals (e.g. DVB-T2 or radio stations)
- independent reception of all available programmes for every subscriber
- suitable for use with Quad and Quattro LNBS
- content: 1x SAT multiswitch

TECHNICAL DATA

Quality	PROFESSIONAL	Power supply	230 V AC
Colour	silver	Power consumption	max. 35 W
Point of use	indoor use	Operating temperature	-10 bis +50 °C
Connections (input)	4x F jack (SAT) 1x F jack (TV/FM)	Power supply unit	integrated
Connections (output)	6x F jack	Weight (set)	device 720 g
Output level (max.)	(typ.) 100 dB μ V (SAT) (typ.) 85 dB μ V (TV/FM)	Dimensions (width)	321 mm
Frequency range	950 - 2150 MHz (SAT) 47 - 862 MHz (TV / radio)	Dimensions (height)	120 mm
Transmission loss	(typ.) 7 dB (SAT) (typ.) 22 dB (TV/FM)	Dimensions (depth)	58 mm
		Packaging	clamshell SF