



★ ★ ★  
PROFESSIONAL



## SAT Multi Switch 5 → 8

This SCHWAIGER® multi switch is used to distribute digital signals of 1 satellite position to up to 8 subscribers. You can feed signals from a Quad or Quattro LNB as well as terrestrial signals. All subscribers can make use of

the entire range of programmes independently from one another.



### ARTICLE INFORMATION

Article Nr SEW4058 531  
EAN 4004005405842



Last updated: 24.07.2019



## FEATURES (SEW4058 531)

- multi switch distributes 1 satellite position to 8 outputs
- can be fed with terrestrial signals (passive)
- independent reception of all available programmes for every subscriber
- suitable for use with Quad and Quattro LNBs
- content: 1x SAT multiswitch

## TECHNICAL DATA

Quality	PROFESSIONAL
Colour	black/silver
Point of use	indoor use
Connections (input)	4x F jack (SAT) 1x F jack (TV/FM)
Connections (output)	8x F jack (SAT)
Output level (max.)	(typ.) 100 dB $\mu$ V (SAT) (typ.) 85 dB $\mu$ V (TV/FM)
Frequency range	950 - 2150 MHz (SAT) 47 - 862 MHz (TV/FM)
Changeover	13/18V/22KHz
Transmission loss	(typ.) 8 dB (SAT) (typ.) 22 dB (TV/FM)

Power consumption	through LNB (max.) 600 mA
Power supply	230 V AC
Power consumption	max. 35 W
Operating temperature	-10 bis +50 °C
Power supply unit	integrated
Weight (set)	device 750 g
Dimensions (width)	360 mm
Dimensions (height)	120 mm
Dimensions (depth)	58 mm
Packaging	clamshell SF