



RECEIVER

Full HD 1080p



FULL HD SAT Receiver

Free To Air (FTA)

This SCHWAIGER® satellite receiver is suitable for reception of all unencrypted TV and radio stations via satellite. Signals are transmitted to the TV in standard quality via the SCART connection and in HD quality via the HDMI connection. The receiver offers all

standard functions for facilitating set up and use. Software updates can be conducted with a USB thumb drive or directly from the satellite (OTA).



ARTICLE INFORMATION

Article Nr DSR576HD
EAN 4004005542400



Last updated: 16.03.2017



(DSR576HD)

- HDTV & SDTV SAT receiver
- AC 3 - Dolby Digital Surround Sound
- pre-programmed channel list (ASTRA 19.2°)
- USB interface for service purposes only
- 7-day Electronic Programme Guide (EPG) (dependent on channel)
- environmentally friendly due to low consumption in sleep mode
- multilingual screen menu
- indication of signal strength and signal quality for best-possible antenna alignment
- event timer can be programmed via EPG
- multifunctional timer
- Super Fast Teletext
- content: receiver, remote control, 2x battery (1.5 V LR03 (AAA)), user manual

TECHNICAL DATA

Type of receiver	SAT (DVB-S2)
Display	4-digit LED display (7 segments)
Programme memory	3000
LNB IN (F-type)	1x (back)
USB 2.0 port	1x (front)
HDMI™ connection	1x (back)
Resolution	576i/576p/720p/1080i/Full HD 1080p
SCART connection	1x (back)
Digital sound output	1x (back) coaxial, S/PDIF
Control function	Unicable (SCR)/DiSEqC 1.0/1.1

Software update	via USB
Input frequency	950 - 2150 MHz
Power supply	176 - 264 V AC , 50 Hz
Power consumption	< 0,5 W in sleep mode < 5 W during operation
Weight (set)	500 g
Colour	black
Dimensions (width)	220 mm
Dimensions (height)	45 mm
Dimensions (depth)	135 mm
Packaging	carton

Last updated: 16.03.2017