



RECEIVER

Full HD 1080p



FULL HD Satellite Receiver

Free to Air (FTA)

This SCHWAIGER® satellite receiver can receive all unencrypted TV and radio stations via satellite and transmits the signals to the TV. Signal transmission is made in standard quality via the SCART connection and in HD quality via the HDMI connection. The receiver

is equipped with a Time Shift Function which can be used when an external memory device is connected. Software updates can be conducted via USB thumb drive.



ARTICLE INFORMATION

Article Nr DSR585HD
 EAN 4004005615999



Last updated: 30.08.2018



FEATURES (DSR585HD)

- HDTV & SDTV SAT receiver
- AC3 - Dolby Digital Surround Sound
- Time Shift Mode (only in combination with an external memory device)
- pre-programmed channel list (ASTRA 19.2°)
- 7-day Electronic Programme Guide (EPG) (dependent on channel)
- environmentally friendly due to low consumption in sleep mode
- multilingual screen menu
- indication of signal strength and signal quality for best-possible antenna alignment
- event timer can be programmed via EPG
- multifunctional timer
- teletext
- content: receiver, remote control, 2x battery (1.5 V LR03 (AAA)), user manual

TECHNICAL DATA

Type of receiver	SAT (DVB-S2)
Display	4-digit LED display
Programme memory	5000
LNB IN (F-type)	1x (back)
USB 2.0 port	1x (back)
HDMI® Connection	1x (back)
Resolution	576p/720p/1080i/Full HD 1080p
SCART connection	1x (back)
Digital sound output	1x (back) optical, S/PDIF
SAT Finder	optical
Control function	DiSEqC 1.0/1.2
Software update	via USB
Power switch	flip-switch, non-illuminated

Remote control	yes
Operating temperature	5 - 35 °C
Input frequency	950 - 2150 MHz
Power supply	230 V, 50 Hz
Power consumption	in sleep mode < 0,5 W during operation < 5 W
Weight (set)	400 g
Colour	black
Dimensions (width)	218 mm
Dimensions (height)	120 mm
Dimensions (depth)	40 mm
Packaging	carton