



RECEIVER

Full HD 1080p
HDMI
HIGH-DEFINITION MULTIMEDIA INTERFACE

ECO
ENERGIESPARER
12 VDC
MOBIL
TIME SHIFT
UNICABLE TECHNOLOGY
UPDATE
by USB

FULL HD Satellite Receiver

Free To Air (FTA)

Thanks to its compact design, this SCHWAIGER® satellite receiver is perfect for use when camping or as a second device for your home. The Unicable-capable receiver is ideal for 12 V operation and has the Time Shift function when an external storage

medium is connected. Thanks to the built-in media player, music, pictures and movies can also be played back. The TV can easily be connected via SCART or HDMI, software updates are conveniently done via USB.

ARTICLE INFORMATION

Article Nr DSR812HD
EAN 4004005031942



Last updated: 04.02.2021



FEATURES (DSR812HD)

- HDTV & SDTV SAT receiver
- reception of unencrypted digital radio and TV channels (FTA)
- suitable for LNB, motorized antenna or Unicable operation
- suitable for 12 volts operation with vehicle power cable
- multilingual screen menu
- 7-day Electronic Programme Guide (EPG) (dependent on channel)
- pre-programmed channel list (ASTRA 19.2°)
- video text (OSD) with subtitle function
- All Channels list and Favourite Channels list
- media player for music, pictures and movies integrated
- automatic channel scan (Fast Auto Scan)
- indication of signal strength and signal quality for best-possible antenna alignment
- automatic aspect ratio detection (4:3 \leftrightarrow 16:9)
- supports Unicable DCSS-LNB up to 8 participants
- scope of delivery: HDTV receiver, remote control, 2x battery (1.5 V LR03 (AAA)), 12 V DC power supply, 12 V DC car connection cable, instruction manual

TECHNICAL DATA

Type of receiver	SAT (DVB-S2)
Display	4-digit LED display (7 segments)
Programme memory	3000
LNB IN (F-type)	1x (back)
USB 2.0 port	1x (front) 1x (back)
HDMI® Connection	1x (back)
Resolution	720 x 576 (PAL)/720 x 480 (NTSC)/ 576i/576p/720p/1080i/Full HD 1080p
SCART connection	1x (back)
Digital sound output	1x (back) coaxial, S/PDIF
RS232 interface	1x (back)
Control function	DiSEqC 1.0/1.1/1.2/1.3/USALS

Software update	via USB
Languages (Menu)	german/english/french/spanish/ turkish
Favourite channels list	16
remote control:	yes
Input frequency	950 - 2150 MHz
Power consumption	in sleep mode <math>< 0,5\text{ W}</math> during operation max. 8 W
Power supply	100 - 240 V AC , 50/60 Hz 12 VDC , 1000 mA
Dimensions (width)	170 mm
Dimensions (height)	40 mm
Dimensions (depth)	110 mm
Packaging	carton