



## LED Light Bulb (E27)

as dimmable light

This LED light bulb creates a pleasant atmosphere due to the adjustable light intensity. The SCHWAIGER<sup>®</sup> LED light bulb can simply replace common light bulbs (E27 socket). In addition to the HOME4YOU network, it can also be integrated into various other Zigbee gateways such as Osram, Philips or Ikea and

can then be controlled with the respective app. Alternatively, the LED light bulb can also be operated with the remote control (ZHF02-MK). The remote allows for operating up to 16 light bulbs at the same time and also has a function for creating individual groups of light bulbs.



### ARTICLE INFORMATION

Article Nr  
EAN

HAL100  
4004005605402



Last updated: 10.09.2018



## FEATURES (HAL100)

- dimmable light
- adjustable light intensity (brightness)
- operation with the SCHWAIGER App via gateway or directly via remote control (ZHF02-MK)
- content: light bulb, user manual

## TECHNICAL DATA

Integrated protocols	ZigBee v3.0
Energy efficiency	A+
Colour shade	warm white
Lumen	806 Lm
Energy consumption	9 kWh / 1000 h
Start-up time	< 1 s
Base	E27
Performance	9 W
Corresponds to old	60 W
Kelvin	2,700 K
Reflected beam angle	240 °

Dimmable	yes
Service life	25000 h
Switching cycles	25000 x
Operating temperature	-20 bis 40 °C
Power supply	220 - 240 V AC , 50/60 Hz
Colour	white
Dimensions (width)	60 mm
Dimensions (height)	120 mm
Dimensions (depth)	60 mm
Packaging	carton